

ALASKA 200 START 230V 12-24V





Battery charger and maintainer with electronic control of the charging current, automatic interruption and restart (TRONIC), for charging lead-acid batteries with 12/24V voltage of motorcycles, vehicles, vans, light trucks. Charge options: normal CHARGE, BOOST quick charge, automatic TRONIC charge and maintenance of WET,GEL,AGM: SPIRAL,MF, START-STOP batteries. Characteristics: choice of CHARGE, TRONIC mode * visualization of charging current (CHARGE) * warning LED to indicate battery charge status, end of charge, maintenance (TRONIC) *choice of outputvoltage, charge voltage, start * protection against overloads and polarity reversal.















AUTOMOTIVE













Norms:

| CODE | V _{ph} = V50/60Hz | A EFF | A EN | C MIN/MAX Ah15h | | cm(L,W,H) | kg kg | BAR | pz/pallet |
|--------|--|--------------|-------------|-----------------------|---|--------------------|----------|--------------------|-----------|
| 807577 | 230 1 ph | 23 12 | 15 8 | 25 30 300 - 160 | 2 | 24,5 19,5 13 | 7,57 | 8004897948 49 2 | 72 |
| | | | | | | | | | |